

ADC-V622-WELL

SPECIFICATIONS

RECORDING COMPRESSION

H.264

IMAGE SENSOR

1/2.9" CMOS, 6.8 MP, 3096 x 2202

LENS / ANGLE OF VIEW

1.62 mm, F2.3, 180°

LOW-LIGHT SENSITIVITY

0 lux with IR

IR RANGE

Up to ~15 feet (5 m)

IMAGE ADJUSTMENTS

Flip, brightness, contrast, saturation, sharpness, exposure

WIRELESS CONNECTIVITY

802.11 b/g/n, 2.4 & 5 GHz

OPERATING TEMPERATURE

32°F - 104°F (0°C - 40°C)

OPERATING HUMIDITY

20% - 80% (non-condensing) RH

MAX POWER CONSUMPTION

12V DC, 12W

DIMENSIONS (L x W x H)

3.125 x 3.125 x 5.2" (7.9 x 7.9 x 13.2 cm)

REQUIREMENTS

POWER

Power over Ethernet or 12V DC power adapter (included)

NETWORK

Wi-Fi (2.4 or 5 GHz) or Ethernet connection to broadband Internet



Wellcam

Wellcam™ empowers safe and healthy independent living by extending wellbeing to everyone in your family. With its Bluetooth speaker, microphone, 180-degree camera, and Two-Way Audio calling, Wellcam makes it easy to create a 24/7 direct connection to family, friends, or caregivers. One press of Wellcam's call-out button is all it takes to reach out and send notifications to everyone on your call list, who then use a mobile app to see and speak with their loved one. Family and caregivers can also use the mobile app to see activity highlights, check in anytime, and receive automatic notifications when Wellcam detects unexpected behavior. Wellcam is the intelligent care companion that gives families peace of mind and extends Alarm.com service to loved ones anywhere, ensuring they feel safe and watched over.

FEATURES

- Wide-angle 180° field of view
- Digital pan / tilt / zoom
- Built-in Bluetooth speaker
- Two-Way Audio with push to call
- Power over Ethernet or Wi-Fi (2.4GHz or 5GHz)
- Works with the Alarm.com customer website and mobile app

INCLUDED ACCESSORIES

- Power Adapter
- Quick Installation Guide
- Things to Try Guide
- Mounting Hardware

LED GUIDE

	LED STATUS	DESCRIPTION
STATUS LED 	Off	Power off
	Flashing Red	Power on, camera booting
	Flashing Green	Local network connection
	Solid Green	Connected to Alarm.com
	Blinking Blue	WPS mode
	Blinking White	Wi-Fi Access Point mode
	Solid White	Call originated from Wellcam answered
TROUBLE CONDITION	Solid Red	No local or Internet connection
FACTORY RESET	Alternating Red and Green	Camera resetting to factory default